

CLAIMS

1. An apparatus comprising:

a first circuit configured to generate a data output signal in response to (i) a data input signal comprising a series of words, (ii) a valid word signal, and (iii) a select signal; and

5 a second circuit configured to generate said select signal in response to (i) said valid word signal, (ii) a start of frame signal, (iii) an end of frame signal and (iv) said data output signal, wherein said select signal adjusts a starting point of each of said words to match a starting point of said first word.

2. The apparatus according to claim 1, wherein said second circuit generates said select signal in further response to a clock signal.

3. The apparatus according to claim 1, wherein said first circuit comprises a data circuit and said second circuit comprises a control circuit.

4. The apparatus according to claim 1, wherein said first circuit comprises:

a first and a second register configured to arrange one or more bits of said data input signal; and

5 a multiplexer circuit configured to present said data output signal in response to said arranged bits.

5. The apparatus according to claim 4, wherein said second register includes a data input configured to receive an output of said first register.

6. The apparatus according to claim 4, wherein said first register and said second register are configured to receive said valid word signal.

7. The apparatus according to claim 1, wherein said second circuit comprises:

a decoder configured to present a length signal in response to said data output signal;

5 a subtractor configured to present a sum signal in response to said length signal and a first enable signal; and

an adder circuit configured to generate said select signal in response to said sum signal.

8. The apparatus according to claim 1, wherein said data input signal, said valid word signal, said start of frame signal and said end of frame signal are received from a data source.

9. The apparatus according to claim 7, wherein said second circuit further comprises a finite state machine configured to control said subtractor and said adder.

10. The apparatus according to claim 9, wherein said second circuit further comprises:

a sum circuit configured to process said sum signal before said adder circuit generates said select signal.

11. The apparatus according to claim 10, wherein said sum circuit presents an end message signal to said finite state machine.

12. A method for adjusting messages in hardware comprising:

(A) generating a data output signal in response to (i) a data input signal comprising a series of words, (ii) a valid word
5 signal, and (iii) a select signal; and

(B) generating said select signal in response to (i) said valid word signal, (ii) a start of frame signal, (iii) an end of frame signal and (iv) said data output signal, wherein said select signal adjusts a starting point of each of said words to
10 match a starting point of said first word.

13. An apparatus comprising:

means for generating a data output signal in response to (i) a data input signal comprising a series of words, (ii) a valid word signal, and (iii) a select signal; and

5 means for generating said select signal in response to (i) said valid word signal, (ii) a start of frame signal, (iii) an end of frame signal and (iv) said data output signal, wherein said select signal adjusts a starting point of each of said words to match a starting point of said first word.